

R 602 V B



D	Number of meals per service	20 to 100
	Quantity per batch in cutter function	Up to 7.7 lbs

A SALES FEATURES

The R 602 V B Bowl Cutter Mixer is ideal for grinding, mincing and kneading, as well as for making mousses, emulsions and smooth stuffings. It effortlessly performs even the lengthiest task in just a few minutes, consistently producing a flawless end product.

B TECHNICAL FEATURES

R 602 V B Bowl Cutter Mixer. Single phase 120/60/1. Power 3 HP. Variable speed : 370 - 3450 rpm. 7 qt. cutter bowl in stainless steel and smooth bowl-base blade assembly. 20 to 100 meals.

Select your options at the back page, **F** part.

C TECHNICAL DATA

Output power	3 HP
Electrical data	120V/60/1 - 15 Amp
Variable speed	370 - 3450 rpm
Dimensions (WxDxH)	20 13/16" x 13 11/16" x 11"
Rate of recyclability	95%
Net weight	77 lbs
Nema #	5-15P
Reference	R 602 V B 120V/60/1

E PRODUCT FEATURES / BENEFITS

MOTOR BASE

- Direct drive induction motor (no belt) for intensive use.
- Power 3 HP
- Stainless steel motor shaft.
- Motor base made from heavy-duty composite material.
- Magnetic safety system, thermal failsafe.
- **Variable Speed:** 370 - 3450 rpm.

CUTTER FUNCTION

- 7 qt. stainless-steel cutter bowl with handle for better grip
- Bowl-base high resistance smooth blade assembly for homogeneous processing even for small amounts
- Central lid opening for adding liquid or solid ingredients during processing
- High heat- and shock-resistant see-through lid to monitor processing from start to finish
- All parts are dishwasher-safe and can easily be removed for cleaning

ACCESSORIES INCLUDED

- Cutter attachment: lid, bowl, and high resistance stainless steel smooth blade assembly with removable cap.

STANDARDS

ETL electrical and sanitation Listed/ cETL (Canada)



R 602 V B

F OPTIONAL ACCESSORIES

- Coarse serrated blade assembly for kneading and grinding, ref 27125
- Fine serrated blade assembly for chopping herbs and spices, ref 27352



Coarse-serrated



Fine-serrated

G ELECTRICAL DATA

120V/60/1 - delivered with cord and plug.

